

Special



Image for illustrative purpose only

概要

見積もりを依頼する

fiber optic

Customer Drawing

Nb of contacts Fiber optic	1
Plug	Plug - Straight
Locking system	Push-pull
Size	00

https://www.lemo.com/int_jp/fgg-00-bb4-ccb10n.html

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.

Technical details

Electrical Configuration

Nb of contacts Fiber optic	1
Insert configuration value	FO/BB4 - 1 FO 126 um hole
Insulator	C: Zirconia Ceramic
Core/Cladding (um)	50/125
Ferrule Material	Zirconia Ceramic
Hole dia.(um)	126

Form & Material

Shell style / Model id	FG - Straight plug key (G) or (B) with bend relief included
Plug	Straight
Housing material	Brass (chrome plated [SAE AMS 2460]) shell and collet nut, nickel plated [SAE AMS QQ N 290] brass latch sleeve and mid pieces
Locking system	Push-pull
Keying	G: 1 key (alpha=0, plug: male contacts, receptacle: female contacts)
Colour	Grey
Weight	7.66 g

Environment

Environmental sealing (IP rating)	IP50
Salt Spray Corrosion	>1000 hr

Cable fixation

Cable termination protection	Standard back nut (no additional protection)
Fixation type	T type cable adapter

https://www.lemo.com/int_jp/fgg-00-bb4-ccb10n.html

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.

Lemoの推奨品

Accessories

Compatible cap

[BFG.00.100.PCSG](#)

https://www.lemo.com/int_jp/fgg-00-bb4-ccb10n.html

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.