



Image for illustrative purpose only

Summary

[Request a quote](#)

[Catalog](#)

| | |
|--------------------------------|--------------------------------|
| Number of contacts Low Voltage | 1 |
| Wire Size/AWG | 26 - 22 |
| Size | 1B |
| Suggested matching part | FGG.1B.555.ZZC |
| Series | B - Indoor keyed |

https://www.lemo.com/int_en/solutions/originals/b-indoor-keyed/egg-1b-655-zzm.html

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.

Technical details

Electrical Configuration

| | |
|---------------------------------|---------|
| Number of contacts Low Voltage | 1 |
| Contact Termination Low voltage | Crimp |
| Contact Dia. | 0.7 |
| Wire Size/AWG | 26 - 22 |

Form & Material

| | |
|------------------------|--|
| Shell style / Model id | EG - Female crimp contact, standard barrel |
| Housing material | Gold plated [ISO 27874] bronze |
| Keying | No keying |
| Weight | 0.11 g |

Environment

| | |
|-----------------------------------|--|
| Technical domain | Audio Video, Energy and Industrial, Medical, Semiconductor, Specialties and Other, Test and Measurement, Transportation, Aerospace and UAV |
| Environmental sealing (IP rating) | No IP rating |
| Temperature range | -55°C / +250°C (max. temperature valid for short periods of use.) |
| Humidity (max) | <=95% [at 60 deg C /140 F] |

Recommended By Lemo

Tools

| | |
|-------------|--------------------------------|
| Positionner | DCE.91.071.BVM |
| Crimp tool | DPC.91.701.V |

https://www.lemo.com/int_en/solutions/originals/b-indoor-keyed/egg-1b-655-zzm.html

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.