



## Summary

[Request a quote](#)

[Catalog](#)

Number of contacts Low Voltage	1
Wire Size/AWG	20 - 18
Size	3B
Matching parts	<a href="#">EGG.3B.665.ZZM</a>
Series	B - Indoor keyed

## Technical details

### Electrical Configuration

Contact Termination Low voltage	Crimp
Contact Dia.	1.3
Number of contacts Low Voltage	1
Wire Size/AWG	20 - 18

### Form & Material

Shell style / Model id	FG - Male crimp contact, standard barrel
Housing material	Gold plated [ISO 27874] brass
Keying	No keying
Weight	0.69 g


[https://www.lemo.com/int\\_en/solutions/originals/b-indoor-keyed/fgg-3b-565-zzc.html](https://www.lemo.com/int_en/solutions/originals/b-indoor-keyed/fgg-3b-565-zzc.html)

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.

## Environment

Technical domain	Audio Video, Energy and Industrial, Medical, Semiconductor, Specialties and Other, Test and Measurement, Transportation, Aerospace and UAV
Environmental protection (IP rating)	No IP rating
Minimal temperature	-55°C / +250°C
Climatical Category	50/175/21
Humidity (max)	<=95% [at 60 deg C /140 F]
Shielding (min)	75 dB (10 MHz)
Shielding (min)	40 dB (1 GHz)
Shock Resistance	100 g [ 6 ms]
Vibration	15 g [10 Hz - 2000 Hz]
<b>Cable fixation</b>	
Cable termination protection	Standard back nut (no additional protection)

## Drawings



No keying

## Dimensions

	A	C
mm.	1.3	1.4
in.	0.05	0.06

[https://www.lemo.com/int\\_en/solutions/originals/b-indoor-keyed/fgg-3b-565-zzc.html](https://www.lemo.com/int_en/solutions/originals/b-indoor-keyed/fgg-3b-565-zzc.html)

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.