## AFF.T7.675.CTA





Image for illustrative purpose only

# **Summary**

Request a quote

Catalog

Nb of contacts Triax	1
Locking system	Push-pull
Size	Τ7


#### https://www.lemo.com/int\_en/aff-t7-675-cta.html

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.

# **Technical details**

Electrical Configuration	
Nb of contacts Triax	1
Contact Termination Triax	Solder
Rated current	12 A
ОНМ	75
Form & Material	
Shell style / Model id	AFF - Adapter plug-plug
Housing material	Brass (chrome plated [SAE AMS 2460]) shell and collet nut, nickel plated [SAE AMS QQ N 290] brass latch sleeve and mid pieces
Locking system	Push-pull
Keying	Circular, male
Colour	Grey
Weight	90.63 g
Environment	
Environmental sealing (IP rating)	IP68
Endurance	>1000 mating cycles
Temperature range	-55°C / +250°C (max. temperature valid for short periods of use.)
Humidity (max)	<=95% [at 60 deg C /140 F]
Shock Resistance	100 g [ 6 ms]
Vibration	15 g [10 Hz - 20000 Hz]
Salt Spray Corrosion	>1000 hr
Cable fixation	
Cable termination protection	Standard back nut (no additional protection)

# **Drawings**



https://www.lemo.com/int\_en/aff-t7-675-cta.html

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.

### **Dimensions**

	Α
mm.	23.5
in.	0.93

### https://www.lemo.com/int\_en/aff-t7-675-cta.html

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.