

Image for illustrative purpose only

Summary

Request a quote Catalog Nb of contacts Triax 1 Carliest / December also

Socket / Receptacle	Socket / Receptacle - Fixed Panel Front Mounted			
Locking system	Push-pull			
Size	Τ7			
Suggested matching part	FAZ.T7.675.CTA06C			

https://www.lemo.com/int_en/paz-t7-675-ctl06c.html

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.


Technical details

Nb of contacts Triax	1
Contact Termination Triax	Solder
Rated current	12 A
ОНМ	75
Form & Material	
Shell style / Model id	PAZ - Fixed socket, collet clamp, nut fixing
Socket / Receptacle	Fixed Panel Front Mounted
Housing material	Brass (chrome plated [SAE AMS 2460]) shell and collet nut, nickel plated [SAE AMS QQ N 290] brass latch sleeve and mid pieces
Locking system	Push-pull
Keying	Circular, female
Colour	Grey
Weight	168.83 g
Environment	
Environmental sealing (IP rating)	IP68
Endurance	5000 mating cycles
Temperature range	-55°C / $+250$ °C (max. temperature valid for short periods of use.)
Humidity (max)	<=95% [at 60 deg C /140 F]
Shock Resistance	100 g [6 ms]
Vibration	15 g [10 Hz - 20000 Hz]
Salt Spray Corrosion	>1000 hr
Cable fixation	
Cable termination protection	Standard back nut (no additional protection)

Drawings

https://www.lemo.com/int_en/paz-t7-675-ctl06c.html

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.



Dimensions

	Α	В	С	E	Μ	L	S1	S2	е
mm.	23.5	30	34	9	24.5	84	22	20	M25x1.0
in.	0.93	1.18	1.34	0.35	0.96	3.31	0.87	0.79	

https://www.lemo.com/int_en/paz-t7-675-ctl06c.html

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.